

SMTP Error Codes and Messages

Error Code Name	Error Code Hex	Error Code Decimal	Error Meaning	Message Text
NORMAL	X'00'	0	NORMAL RETURN CODE	None.
ERRNOCA	X'01'	1	NO COMMAREA ERROR	ROPES0040 - ROPES MODULE ROPEMRDP WAS CALLED WITHOUT A COMMAREA.
ERRBDCL	X'02'	2	BAD CALL TYPE	ROPES0041 - ROPES MODULE WAS CALLED WITH AN INVALID CALL/REQUEST TYPE.
ERRICSQ	X'03'	3	IMPROPER CALL SEQUENCE ERROR	ROPES0042 - IMPROPER CALL SEQUENCE DETECTED, MAIL HEADER ALREADY SENT.
ERRSYNT	X'04'	4	SMTP OPTION SYNTAX ERROR	ROPES0043 - SYNTAX ERROR IN SMTP OPTION GIVEN BY QBR-MISSING CLOSE PARENTHESIS.
ERRMHST	X'05'	5	MISSING SENDING HOST SMTP PARM	ROPES0044 - MISSING SMTP SENDING HOST PARAMETER VALUE FROM THE INITIAL QBR.
ERRMMFR	X'06'	6	MISSING MAILFROM SMTP PARM	ROPES0045 - MISSING MAILFROM PARAMETER VALUE FROM THE INITIAL QBR.
ERRMRCT	X'07'	7	MISSING RCPTTO SMTP PARM	ROPES0046 - MISSING RCPTTO PARAMETER VALUE FROM THE INITIAL QBR.
ERRMSUB	X'08'	8	MISSING SUBJECT SMTP PARM	ROPES0047 - MISSING SUBJECT PARAMETER VALUE FROM THE INITIAL QBR.
ERRNINQ	X'09'	9	INQUIRE SYSTEM FAILED	ROPES0048 - AN EXEC INQUIRE SYSTEM FOR JOBNAME FAILED.
ERREINA	X'10'	16	INITAPI REQUEST FAILED	ROPES0049 - EZASOKET CALL FOR INITAPI FAILED WITH ERROR CODE = XXXXX.
ERRGSK	X'11'	17	GET SOCKET CALL FAILED	ROPES0050 - EZASOKET CALL FOR SOCKET FAILED WITH ERROR CODE = XXXXX.
ERRGHST	X'12'	18	GETHOSTBYNAME CALL FAILED	ROPES0051 - EZASOKET CALL FOR GETHOSTBYNAME FAILED WITH ERROR CODE = XXXXX.
ERRECON	X'13'	19	CONNECT FAILED	ROPES0052 - EZASOKET CALL FOR CONNECT FAILED WITH ERROR CODE = XXXXX.
ERRRDSK	X'14'	20	READ SOCKET FAILED	ROPES0053 - EZASOKET CALL FOR READ SOCKET FAILED WITH ERROR CODE=XXXXX.
ERRWTSK	X'15'	21	WRITE SOCKET FAILED	ROPES0054 - EZASOKET CALL FOR WRITE SOCKET FAILED WITH ERROR CODE=XXXXX.
ERRSOKR	X'16'	22	ERROR IN SOCKET RESPONSE	ROPES0055 - AN ERROR SMTP RESPONSE WAS RECEIVED CODE = XXX.
ERRCLSK	X'17'	23	ERROR CLOSING SOCKET	ROPES0056 - EZASOKET CALL FOR CLOSE SOCKET FAILED WITH ERROR CODE=XXXXX.
ERRLBHD	X'18'	24	ERROR CLOSING SOCKET	ROPES0057 - SMTP OPTIONS MISSING OR INVALID AS OF LAST CALL-MAIL NOT SENT.
N/A	N/A	501	INVALID PARAMETERS	ROPES0058 - E-MAIL ADDRESS INVALID FOR REPORT=nnnnnnnn, PRINTER=nnnn ADDRESS:

IP Error Codes and Messages For LPR and Direct Socket Printing

Error Code Name	Error Code Hex	Error Code Decimal	Error Meaning	Message Text
NORMAL	X'00'	0	NORMAL RETURN CODE	None
ERRNOCA	X'01'	1	NO COMMAREA ERROR	ROPES0060 - ROPES module ROPELPRP was called without a COMMAREA.
ERRBDCL	X'02'	2	BAD CALL TYPE	ROPES0061 - ROPES module was called with an invalid Call/Request type.
ERRICSQ	X'03'	3	IMPROPER CALL SEQUENCE ERROR	ROPES0062 - Improper call sequence detected.
ERROPTF	X'04'	4	ERROR READING OPTIONS FILE	ROPES0063 - LPR Options Record was not found or error encountered reading file.
ERRMHST	X'05'	5	MISSING SENDING HOST NAME	ROPES0064 - Sending Host Name parameter value is missing or invalid.
ERRNODT	X'06'	6	ERROR NO DATA RECEIVED	ROPES0065 - Some output data was expected but none was received.
ERRSKOP	X'07'	7	SET SETSOCKOPT FAILED	ROPES0066 - EZASOKET call for SETSOCKOPT failed with error code = xxxxxx.
ERRSELE	X'08'	8	SELECT FAILED	ROPES0067 - SELECT failed on xxxxxx function - error code = xxxxxx.
ERRNIQ	X'09'	9	INQUIRE SYSTEM FAILED	ROPES0068 - An EXEC INQUIRE SYSTEM for JOBNAME failed.
ERREINA	X'10'	16	INITAPI REQUEST FAILED	ROPES0069 - EZASOKET call for INITAPI failed with error code = xxxxxx.
ERRGSOK	X'11'	17	GET SOCKET CALL FAILED	ROPES0070 - EZASOKET call for SOCKET failed with error code = xxxxxx.
ERRGHST	X'12'	18	GETHOSTBYNAME CALL FAILED	ROPES0071 - Unable to resolve ROLI panel remote host to IP address or host name.
ERRECON	X'13'	19	CONNECT FAILED	ROPES0072 - EZASOKET call for CONNECT failed with error code = xxxxxx.
ERRRDSK	X'14'	20	READ SOCKET FAILED	ROPES0073 - EZASOKET call for READ SOCKET failed with error code=xxxxxx.
ERRWTSK	X'15'	21	WRITE SOCKET FAILED	ROPES0074 - EZASOKET call for WRITE SOCKET failed with error code=xxxxxx.
ERRLPDR	X'16'	22	ERROR IN LPD RESPONSE	ROPES0075 - An LPD error response was received code = xx.
ERRCLSK	X'17'	23	ERROR CLOSING SOCKET	ROPES0076 - EZASOKET call for CLOSE SOCKET failed with error code=xxxxxx.
ERRTMEQ	X'18'	24	SELECT TIME OUT	ROPES0077 - A SELECT request timed out for a xxxxxx SOCKET function.
ERRRHXL	X'19'	25	REMOTE HOST NAME TOO LARGE	ROPES0078 - Remote host name exceeds 39 characters in length.
ERRFLSZ	X'1A'	26	DATA CTR DOES NOT MATCH SENT	ROPES0079 - Calculated report size does not match amount of data sent.
ERRMRPR	X'1B'	27	MISSING REQUIRED PARAMETERS	ROPES0120 - Required LPR options are missing for Printer = xxxx-Report=xxxxxxxx.
ERRXLAT	X'1C'	28	TRANSLATE OPTIONS ERROR	ROPES0121 - Translation options are not valid. Function = x, RC = xx, Reason = xx.
ERRGADR	X'1D'	29	GETADDRINFO FAILED	ROPES0122 - EZASOKET call for GETADDRINFO failed with error code = xxxxxx.
ERRPTON	X'1E'	30	PTON FAILED	ROPES0123 - EZASOKET call for PTON failed with error code = xxxxxx.
ERRNOV6	X'1F'	31	NO V6 SUPPORT	ROPES0124 - ROLI host type indicates IPv6 host but IPv6 support disabled in ROPES.
ERRGAV6	X'20'	32	V6 ADDR BUT NO V6 SUPPORT	ROPES0125 - Host name resolves to an IPv6 address. IPv6 support disabled in ROPES.